

Overview of the Cell Terminal Connectors and the Compatibility Guide

Product length	Cell profile	Cell Dimensions	SE40AHA-CON 47 mm, M6	SE60AHA-CON 50 mm, M6	SE100AHA-CON 68 mm, M8	SE180AHA-CON 70 mm, M8	SE70AHA-CON 61 mm, M6	SE130AHA-CON 50 mm, M6	CA180AHA-CON 70 mm, M8	SE400AHA-CON 65 mm, M14	SP-LFP60CON 38 M6	SP-LFP100CON 61 mm, M8	SP-LFP200CON 70 mm, M8	LFP040-CON 47 mm, M6	LFP060-CON 61 mm, M6	LFP090-CON 61 mm, M8	LFP100-CON 68 mm, M8	LFP020-CON 61 mm, M8	LFP200-CON 66 mm, M12	LFP160-CON 70 mm, M8	LFP200-CON-B (TALL) 100 mm, M8	LFP300-CON 56 mm, M12	LFP400-CON 65 mm, M14	LFP700-CON 69 mm, M14	LFP1000C-CON 63 mm, M14	GBS 20 AH 47 mm, M4	
SE40AHA	CALB 40Ah	181 x 115 x 46	OK											OK													
SE60AHA	CALB 60Ah	217 X 142 X 50		OK					OK(#A)																		
SE100AHA	CALB 100Ah	218 x 145 x 68			OK													OK									
SE180AHA	CALB 180Ah	279 x 182 x 71				OK			OK				OK														
SE70AHA	CALB 70Ah	206 x 115 x 61					OK								OK	OK(#A)			OK(#A)								
SE130AHA	CALB 130Ah	278 x 182 x 56		OK(#A)				OK																			
CA180AHA	CALB 180Ah	279 x 182 x 71				OK			OK				OK														
LFP020AH	GBS 20Ah	152 x 71 x 42										OK(#A)															OK
SE400AHA	CALB 400Ah	449 x 283 x 71							OK			OK															OK(#A)
SP-LFP60AHA-SZ	Singoply 60Ah	222 x 139 x 34																OK									
SP-LFP100AHA	Singoply 100Ah	218 x 143 x 61							OK			OK															
SP-LFP200AHA	Singoply 200Ah	279 x 182 x 71				OK			OK			OK															
LFP040AHA	Winston 40Ah	181 x 115 x 46	OK											OK													
LFP060AHA	Winston 60Ah	206 x 115 x 61				OK								OK	OK	OK(#A)		OK(#A)									
LFP090AHA	Winston 90Ah	218 x 143 x 61										OK				OK											
LFP100AHA	Winston 100Ah	218 x 145 x 68			OK												OK										
LFP200AHA	Winston 200Ah	362 x 256 x 56																	OK						OK(#A)		
LFP160AHA	Winston 160Ah	279 x 182 x 71											OK														
LFP200AHA-B	Winston 200Ah Tall	276 x 183 x 100				OK			OK												OK						
LFP300AHA	Winston 300Ah	306 x 362 x 56																									
LFP400AHA	Winston 400Ah	285 x 461 x 65																			OK(#A)		OK				
LFP1000AHC	Winston 1000Ah	356 x 560 x 126																									
LFP700AHA	Winston 700Ah	295 x 626 x 68																						OK	OK		OK
WN36AH	WINA 36	155 x 130 x 36									OK																
WN50AH	WINA 50	187 x 120 x 47												OK													
WN72AH	WINA 72	206 x 112 x 60																									
WN100AH	WINA 100	230 x 230 x 39																									

NOTES: The distance (in mm) is the spacing between the middle of the holes in the copper terminal connector.
 OK #1 - the holes in the copper terminal must be modified, bigger screws need to be used
 OK #2 - smaller size of the screws must be used
 OK(#A) - this model of the copper terminal connector may be used as an option

<http://www.ev-power.eu>
 EV-Power.eu managed by i4wifl a.s. (member of GWL/Power group)

